



Copyright © 2023, TELTONIKA NETWORKS. Specifications and information given in this document are subject to change by TELTONIKA NETWORKS without prior notice.



HARDWARE

FRONT VIEW



BACK VIEW



RJ45 LED MEANING



POWER SOCKET PINOUT





FEATURES

ETHERNET

ETTERRET	
LAN	5 x ETH ports, 10/100/1000 Mbps, supports auto MDI/MDIX crossover
IEEE 802.3 series standards	802.3i, 802.3u, 802.3ab, 802.3x, 802.3az
POE	
PoE ports	Port 1- 4
PoE standards	802.3af and 802.3at
PoE Max Power per Port (at PSE)	30 W
Total PoE Power Budget (at PSE)	60 W
Maximum Ethernet cable length	100 m
PERFORMANCE SPECIFICAT	IONS
Bandwidth (Non-blocking)	10 Gbps
Packer buffer	128 KB
MAC address table size	2K entries
Jumbo frame support	9216 bytes
POWER	
Connector	2-pin industrial DC power socket
Input voltage range	9 – 30 VDC
PoE-out input voltage range	9 – 30 VDC
Power consumption	Idle: 0.64 W / Max: 2.31 W / PoE Max: 60 W
PHYSICAL INTERFACES	
Ethernet	5 x RJ45 ports, 10/100/1000 Mbps
Status LEDs	1 x Power LED, 10 x LAN status LEDs
Power	1 x 2-pin industrial DC power socket
Other	1 x Grounding screw
PHYSICAL SPECIFICATION	
Casing material	Aluminum housing
Dimensions (W x H x D)	115 x 32 x 95 mm
Weight	384 g
Mounting options	DIN rail or wall mounting (additional kit needed), flat surface placement
OPERATING ENVIRONMENT	r
Operating temperature	-40 °C to 75 °C
Operating humidity	10% to 90% non-condensing
Ingress Protection Rating	IP30
REGULATORY & TYPE APPR	OVALS
Regulatory	CE/RED, UKCA, CB, EAC, RoHS, REACH, ANRT, RCM, GITEKI, FCC, IC, E-mark
SAFETY	
Standards	EN IEC 62368-1:2020+A11:2020



WHAT'S IN THE BOX?

STANDARD PACKAGE CONTAINS

- TSW101
- QSG (Quick Start Guide)
- Packaging box



STANDARD ORDER CODES

PRODUCT CODE	HS CODE	HTS CODE	PACKAGE CONTAINS
TSW101 000000	851762	8517.62.00	Standard package

For more information on all available packaging options - please contact us directly.



TSW101 SPATIAL MEASUREMENTS & WEIGHT

MAIN MEASUREMENTS

0		
Pov: 17:	15 x 32 x 95 mm	
DUX. 17.	73 x 71 x 148 mm	

TOP VIEW

The figure below depicts the measurements of TSW101 and its components as seen from the top:



RIGHT VIEW

The figure below depicts the measurements of TSW101 and its components as seen from the right side:





FRONT VIEW

The figure below depicts the measurements of TSW101 and its components as seen from the front panel side:



REAR VIEW

The figure below depicts the measurements of TSW101 and its components as seen from the back panel side:





MOUNTING SPACE REQUIREMENTS

The figure below depicts an approximation of the device's dimensions when cables and antennas are attached:





DIN RAIL

The scheme below depicts protrusion measurements of an attached DIN Rail:

